



"Multi-Control Association, and then click "+" in the right



wo itemsin the page, one is your main switch, the other is ne one you associate just now. Note: Please confirm the associated switch is

4. Choose the switch that you want to associate to and

the same light. Then go back to previous page you will see

then choose the switch button that you want to control



5. Now you are able to control your light with two Do not associate another button in the same switch for 6. If you want to add another third or more smart switches to control your light, just repeat the steps above. And you will see the result as below when you associate another new



Enter Smart Life Skill in Alexa APP

Scan this QR code

. Complete product networking configuration in the

Complete the device's networking configuration according Complete the device's networking configuration according to the prompts in the App. Note: In the App, change the name of the device to an easily identifiable name such as Alexa; names are usually in English, such as "bed light".

1. Launch Smart Life App, sign into your account and make sure Smart Device is on the device list

2. Minimize Smart Life App, then launch the Alexa App and sign in your Alexa account and make sure you have at least one Alexa smart speaker-controlled device installed like Echo dot, etc.

SERVICE Thank you for your trust and support to our products, we will provide you with a two-year worry-free after-sales service (freight is not included), please do not alter this warranty service card, to safeguard your legitimate rights warranty service card, to safeguard your legitimate rights and interests. If you need service or have any questions, please consult the distributor or contact us. Product quality problems occur within 24 months from the date of receipt, please prepare the product and the packaging, applying for after-sales maintenance in the site or store where you purchase; if the product is demanded that to personal reasons a cortain amount of damaged due to personal reasons, a certain amount of maintenance fee shall be charged for repair.

We have the right to refuse to provide warranty service if:

1. Products with damaged appearance, missing LOGO or beyond the service term

2. Products that are disassembled, injured, privately

repaired, modified or have missing parts 3. The circuit is burned or the data cable or power interface is damaged Products damaged by foreign matter intrusion (including but not limited to various forms of fluid, sand, dust, soot, etc.)

RECYCLING INFORMATION

All products marked with the symbol for separate collection of waste electrical and electronic equipment (WEEE Directive 2012/19 / EU) must be disposed of separately from unsorted municipal waste. To protect your health and the environment, this equipment must be disposed of at designated collection disposed of at designated collection points for electrical and electronic equipment designated by the government or local authorities.

Correct disposal and recycling will help prevent potential negative consequences for the environment and human health. To find out where these collection points are and how they work, contact the installer or your local authority

WARRANTY CARD

Product Information Product Name Product Type Purchase Date Warranty Period_ Dealer Information Customer's Name Customer Phone Customer Address Maintenance Records

Than to have to be a second			
Failure date	Cause Of Issue	Fault Content	Principa



Identify Line/Load Wire(Note:The color of your wire may be different from the color shown on the manual.)

32°C

3. In the upper left corner of Home page, press

0

₹ 9 0 ∆ ≡

search button next to it

the button to show APP Menu. Then select sas in

4. Type in "Smart Life "in the search and press the

★ □ □

***** O A =

Installation must be carried out by a qualified


2. Keep the device out of the reach of children.

3. Keep the device away from water , damp or hot

Install the device away from strong signal sources such as microwave oven that may cause signal interruption resulted in abnormal operation of the

5. Obstruction by concrete wall or metallic materials may reduce the effective operation range of the device and should be avoided.


6. Do NOT attempt to disassemble, repair or modify the device.



7M-104R-M Product Type Smart Switch Module 90-250V AC 50/60Hz 10A/Gang;Total 10A Wireless Protocol zigbee3.0 Operation Temp. -10°C ~ 65°C Operation Range ≤70 m 40x40x18 mm IP Rating IP20 WIRING DIAGRAM

TECHNICAL SPECIFICATIONS

1. With two 1 Gang switch



T¥ Wall Socket T¥ Wall Socket

2. With two 2/3 Way switches

3. With Wall Socket



3.Add the device successfully, you can edit the name

5. Enable Smart Life Smart Skill then sign in your Smart

6. Once your account has been successfully linked, ask Alexa to discover devices. After a 20-second searching

Alexa will show all the available devices

Life account to complete your account set up.

Tops Smert
"Kless, oot hallway light to 50 yersent"

South Life - South Harry
Tallow, have on the air condition

O Secretary

How to reset /pair Wi-Fi code a. For switch module:

Press the reset button on the module for a long time until the beep sounds continuously and quickly for pairing and

b. For rocker light switch:

0 0 0

press the switch button for 20 times (ON/OFF cycle for 10 times) until the beep sounds continuously and rapidly as Di-Di-Di... for pairing and reset mode.

C. For reset switch:

press the switch button for 10 times until the beep sounds continuously and rapidly as Di–Di–Di... for pairing and reset

mode.

7. In the Smart Home page, you can group your devices in

different categories. Your Smart Life APP has now been

through Alexa.

How to achieve multicontrol association (only for N+L wire)

Note: Please confirm you have successfully finished the link method above for adding this switch to your Smart Life App before the association.

1. Add another smart switch to the same Smart Life App. (If there is a smart switch having been added before to the app, just go to next step.)

Note: If your switch requires a neutral wire, then there is no need to wire the new added switch to the light, only L and N are required for wiring. Then you can control 1 light with multiple switches in Smart Life

If your switch doesn't requires a neutral wire, you need to follow the wiring instructions to connect the L and light. At this point,you can control the lights simultaneously with multiple switches. 2. Then you will see two devices in the app and click

the main switch (as one gang switch as below) by entering into the next operation.



Set up device ♠ Create new home £.

①. Launch the Google Home App and make sure Google Home speaker is installed. If not, please follow Google Home speaker installation instruction to complete the

9 0 <u>a</u>

②. Open the Google Home app and click on the plus sign in the top left corner to enter the "add and manage" page, then click on "Set up device".

3. Enter "smart life" in the search box and then search (g). Enter smart line in the search dox and men search for it. Enable smart life smart skills, and then log in to your moes account to complete theaccount setup. After successfully logging into youraccount, you need to wait 20 seconds to search fordevices. Once the device is successfully discovered, it means that your smart life app been paired with Google Home, and all available smart devices are displayed on the homepage upon returning. Now you can use Google Home to cortrol your smart Now you can use Google Home to control your smart